

# Axiom

6KVA ~ 20KVA  
PF 0.9 (3:1)



## Features

- High frequency and true double-conversion
- DSP digital control technology
- Wide input voltage range (110V ~ 300V)
- Output power factor 0.9
- Optimized battery configuration: 192V / 240V
- Cold start
- Auto sensing frequency
- ECO mode operation for energy saving
- 50/60Hz frequency conversion mode
- Selectable output voltage via LCD
- Selectable battery shutdown voltage (EOD) via LCD
- Selectable input mode via LCD (3:1 or 1:1)
- Power-on self test
- Advanced battery management (ABM)
- Short circuit and overload protection
- Automatic charging in OFF mode
- Fan speed auto control when temperatures varies
- Standard RS232 / USB communication port
- Standard emergency power off (EPO)
- Optional RS485 / SNMP / AS400 communication port
- Optional extension battery bank
- Optional battery temperature compensation
- Optional built-in isolation transformer
- Optional manual bypass
- Optional N+X redundancy parallel

## Details

- |             |                              |
|-------------|------------------------------|
| 1. AC Input | 7. EPO                       |
| 2. DC Input | 8. Manual Bypass (optional)  |
| 3. Outlet   | 9. SNMP/AS400 (optional)     |
| 4. Fan      | 10. Breaker                  |
| 5. RS232    | 11. Parallel Card (optional) |
| 6. USB      | 12. BAT_NTC (optional)       |



## Technical specifications

MODEL	AXM 06	AXM 10	AXM 15	AXM 20
Capacity	6 KVA / 5.4 KW	10 KVA / 9 KW	15 KVA / 13.5 KW	20 KVA / 18 KW
<b>INPUT</b>				
Rated voltage	3:1: 360 / 365 / 380 / 400 / 415 Vac; 1:1: 208 / 220 / 230 / 240 Vac (settable via LCD)			
Voltage range	3:1: 190 ~ 277 Vac (derating 50%), 277 ~ 520 Vac (no derating); 1:1: 110 ~ 160 Vac (derating 50%), 160 ~ 300 Vac (no derating)			
Frequency	40 ~ 70 Hz (auto-sense)			
Power factor	3:1 ≥ 0.95; 1:1 ≥ 0.99			
<b>BYPASS</b>				
Voltage range	– 40% ~ +15% (settable)			
Frequency	50 / 60 Hz ± 5 Hz			
<b>OUTPUT</b>				
Voltage	208 / 220 / 230 / 240 Vac (settable via LCD)			
Voltage regulation	± 1%			
Frequency	Synchronized with utility in mains mode; 50 / 60 ± 0.2 Hz in battery mode			
Waveform	Sinusoidal			
Crest factor	3:1			
Harmonic distortion	≤ 2% (linear load); ≤ 5% (non-linear load)			
Transfer time	0 ms			
Overload capability	105% ~ 125%: transfer to bypass in 3 mins; 125% ~ 150%: transfer to bypass in 30 s; > 150%: transfer to bypass in 0.5 s			
<b>EFFICIENCY</b>				
Mains mode	≥ 92%			
Battery mode	≥ 91%			
ECO mode	≥ 98%			
<b>BATTERIES</b>				
DC voltage	192 / 240 Vdc			
Inbuilt battery of standard model	12 V / 7.0 Ah × 16 / 20	12 V / 9.0 Ah × 16 / 20	/	/
Charging current	Standard model	1 A	/	/
	Extensible model	7 A		
Recharge time	Standard model (St): 8 h (90% capacity restored in 3 hours); Extensible model (Ex): depend on the capacity of battery			
<b>ALARMS</b>				
Utility failure	4 s per beep			
Low battery	1 s per beep			
Overload	1 s twice beep			
UPS fault	Long beep			
<b>COMMUNICATIONS</b>				
RS232 / USB (standard)	Supports Windows® 98 / 2000 / 2003 / XP / Vista / 2008 / Windows® 7 / 8 / 10			
SNMP (optional)	Power management from SNMP manager and web browser			
<b>OTHERS</b>				
Humidity	20 ~ 90% RH @ 0 ~ 40°C (non-condensing)			
Noise level	≤ 58 dB (1m)	≤ 60 dB (1m)		
Dimensions (W × D × H) (mm)	262 × 580 × 455 (Ex), 262 × 580 × 732 (St)	262 × 580 × 628 (Ex)		
Packaged dimensions (W × D × H) (mm)	355 × 682 × 615 (Ex), 359 × 687 × 937 (St)	359 × 687 × 832 (Ex)		
Net weight (kg)	25.0 (Ex), 73.0 (St)	25.5 (Ex), 74.0 (St)	38.5 (Ex)	39.0 (Ex)
Gross weight (kg)	28.5 (Ex), 82.5 (St)	29.0 (Ex), 83.5 (St)	47.0 (Ex)	47.5 (Ex)

\* Derate capacity to 70% in CUCF mode and to 90% when the output voltage is adjusted to 208Vac

\* 3:1 means three-phase input and single-phase output mode; 1:1 means single-phase input and single-phase output mode

\* St means standard model, Ex means extensible model

\* All specifications subject to change without notice